

P6000S #CONN #DPP



Main Features		
Frequency	Hz	50
Voltage	V	400
Power factor	cos ф	0.8
Phase		3

Power Rating		
Emergency Standby Power ESP	kVA	6.9
Emergency Standby Power ESP	kW	5.5
Continuous power COP	kVA	5.6
Continuous power COP	kW	4.5

Single Phase Power Rating		
Single phase Maximum Power	kVA	3.2
Single phase continuous power COP	kVA	3.0

Ratings definition (According to standard ISO8528 1:2005)

Engine specifications		
Engine Brand		Yanmar
Model		L100V Electric
[50Hz] Exhaust emission level		Stage V
Engine cooling system		Air
Displacement	cm³	435
Aspiration		Natural
Operating Speed-Nominal	rpm	3000
Speed governor		Mechanical
Fuel		Diesel
Oil capacity		1.6
Starting system		Electric



Alternator Specifications		
Туре		
Class		Н
IP protection		23
Poles		2
Frequency	Hz	50
Voltage regulation system		Compound

Dimensional data		
Length	(L) mm	970
Width	(W) mm	580
Height	(H) mm	927
Dry weight	kg	203
Fuel tank capacity	1	19

Autonomy		
Fuel consumption at 75% of Load	l/h	1.53
Fuel consumption at 100% of Load	l/h	2.04
Running time at 75% of load	h	12.42
Running time at 100% of load	h	9.31

Noise level		
Guaranteed noise level (LWA)	dB(A)	84
Noise pressure level @ 7 m	dB(A)	56

GENSET CONTROL PANELS (CONN DPP)

Mounted on the genset and complete of: instrumentation, control, protection of the generating set and sockets.

COMMANDS

- Start selector switch with key: OFF ON START
- CONNector for AMF/RSS (Accessory available)

INSTRUMENTATION

- Voltmeter

PROTECTIONS

- Circuit breaker
- Differential protection (DPP)
- Engine Protection unit: High engine temperature; Low oil pressure; Low Fuel Level; Battery Charger alternator failure.

SOCKET TYPE





